

Trove2BWC (Battery/Wire Trough Enclosure)

Access & Power Integration Solutions

Altronix Trove2BWC is a dual-purpose enclosure that can be used as wiring troughs or battery cabinets when mounted above or below of the Trove2 integrated power and access solution. The knockouts on the Trove2BWC have been strategically placed to line up with the Trove2 allowing for easy conduit connections between cabinets. Trove2BWC includes cam locks and 2 tamper switches to ensure access to wiring and batteries is secure.

TROVE™



Trove2BWC
with batteries



Trove2BWC
with wires

Specifications

Features

- 16 Gauge powder coated steel
- Convenient knockout configuration:
 - Three (3) single knockouts 2.415" (2" Conduit)
 - Eight (8) double knockouts 1.362" (1" Conduit) / 1.115" (3/4" Conduit)
- Cam lock, tamper switches and mounting hardware included

Capacity

- Accommodates up to four (4) 12VDC/12AH batteries

Physical and Environmental

Dimensions (H x W x D):

21.5" x 7.62" x 6.25" (546.1mm x 193.5mm x 158.8mm)

Weights (approx.):

Product: 10 lb. (4.53 kg)
Shipping: 14 lb. (6.35 kg)

Dimensions and Drawing

Dimensions (H x W x D approximate)

21.5" x 7.62" x 6.25" (546.1mm x 193.5mm x 158.8mm)

